

Q10



Analog Adjustable 3-wire Transmitters



Q10 is a multirange 3-wire temperature transmitter with Pt100 or Pt1000 input and 0-10 V output.

Main applications are in the HVAC sector, where the control systems often require 0-10 V input signals.

Q10 is designed for high reliability and good industrial performance.

The “low profile” housing is extremely durable and facilitates easy connections and adjustments.



- 0-10 V output
- Rangeable with solder pads and potentiometers
- Temperature linear output
- Selectable sensor break function
- Short-circuit protected output
- Polarity protected power supply
- Easy wiring, large center hole
- Moulded electronics for high protection

Specifications:



	Q10 (Pt100)	Q10 (Pt1000)
Input	Pt100 ¹⁾ , 3-wire connection	Pt1000 ¹⁾ , 3-wire connection
Maximum lead resistance	11 Ω / wire	11 Ω / wire
Sensor break	Upscale (>11 V), Downscale (0 V)	Upscale (>11 V), Downscale (0 V)
Adjustments		
Span	50/100/150/200 °C 100/200/300/400 °F	50/100/150/200 °C 100/200/300/400 °F
Fine adjustment	±10 %	±10 %
Zero	-50 to +50 °C -60 to +120 °F	-50 to +50 °C -60 to +120 °F
Output	0-10 V, 3-wire connection	0-10 V, 3-wire connection
Minimum load	10 kΩ	10 kΩ
Short-circuit protection	Yes	Yes
Operating Temperature	-40 to +85 °C / -40 to +185 °F	-40 to +85 °C / -40 to +185 °F
Linearization	Temperature linear output	Temperature linear output
Galvanic isolation	No	No
Power Supply	15 to 30 VDC (polarity protected)	15 to 30 VDC (polarity protected)
Current consumption	12 mA	12 mA
Typical accuracy	±0.15 % of temperature span	±0.15 % of temperature span
Connection head	DIN B or larger	DIN B or larger

¹⁾IEC 60751, α=0.00385

Input connections



Output & power supply connections



Dimensions

